

---

# INSTALLATION

---

## Package description :

The package is made of 2 main folders:

- The « Bin » folder includes the executable for the panels and the demo program,
- The « Doc » folder includes the signals documentation.

The **Bin/Software** folder includes the file **StormAudio.lpz** that should be loaded to the 3 serie processor.

The **Bin/Panel** folder includes two panel templates: a Basic and an Advanced.

## Installation :

1) To install the panels, you need to follow below steps:

- Install Adobe Air runtime: <https://get.adobe.com/fr/air/>
- Go to **GUI/Installation** folder and launch **CrestronXPanel installer.exe**
- Go to folder **GUI/BasicUSer-2.c3prj** and launch **BasicUSer.c3p**
- Go to **option->HostSettings** and adjust the 3 serie processor IP address. With the program loaded in the 3 serie processor, the panel should be able to connect.

2) To load the program, you need to follow below steps:

- Connect via FTP to the 3 serie processor and upload the file **StormAudio.lpz** in program 1 for example.
- Connect using telnet to the 3 serie processor and execute the following command: **progrload -p1**, or if program 2: **progrload -p2**